

PEHRATEK TECHNICAL BULLETIN



XM-5000 VRA 3D TOY

SERIES II

- TWO MOTION ATTRACTORS
- CUSTOM SOUNDS
- 8 LED LIGHT PATTERNS
- CUSTOM BACKGROUNDS
- OPERATES ON BOTH IR OR RF
- POPULAR DISNEY CHARACTERS
- CORNER OR WALL MOUNTED
- BRIGHT BACKLITE

PEHRATEK SMART REMOTE CONTROL

LED FUNCTION INDICATORS

SOFT TOUCH BUTTONS

ALL-ON FEATURE

AVAILABLE IN IR OR RF VERSIONS

ADJUSTABLE ON TIME



10 SELECTABLE SOUNDS

8 LED LIGHT PATTERS

3 MOTION PATTERNS

CENTER BOX CONTROL

QUAD OPERATION FROM ONE REMOTE

CONTROL VRA WITH FOOTPEDAL



CONTROL VRA WITH DESK TOP BUTTON



Pehrtek Products has now added the AI-100 interface module that can be used to operate PEHRATEK VRA systems with the buttons built in an audiometer (Audiostar Pro) Inventis Piano, Interacoustics)

Pehrtek Products are the most versatile and interconnected systems on the market today featuring a wide array of centering units, cochlear implant testing VRAs and are the only product that can operate on both wireless Infra Red and Radio Frequency controls to eliminate interference!




FCC ID:2A6D4XM5000

PEHRATEK PRODUCTS
9285 Pierson Lake Drive
Chaska, MN 55318
866-470-3532



USING CUSTOM MEDIA WITH VDS-3000 **SERIES II**



FILE 2- SRT BOARD



FILE 3-LIVE ANIMALS



FILE 4-ADULT PT INFO

HOW TO UPLOAD CUSTOM FILES ON THE VDS-3000 HD

- 1) Remove SD memory card from underneath unit. (Cover plate has two screws)
- 2) Insert into computer
- 3) Select File number #2, #3, #4 folders to place the new media
- 4) Continue to label the file #2, or #3, or #4 so they can be recalled by the remote
- 5) Reinsert SD memory card into VIDEO VRA and cycle the power
- 6) Select specific folders by pressing FILE button at top of the remote (LED light blinks file number)
- 7) After the file has played the unit will return to the root file (Main cartoon compilation)

FILE PARAMETERS

File Format: .mp4, .avi

Codec: H.264

Resolution: 1920x1080. For best results, match video resolution to monitors native resolution (Generally 1920x1080. Some sizes 1600x900 or 1280x800)

Framerate: 30 frames per second.

Audio Codec: MP3

Sample: 44,100hz 16bit

Bitrate: 128kbps

Channels: 2

www.pehratek.com

